



Staircase time switch TLZ61NP-230V+UC



Only skilled electricians may install this electrical equipment otherwise there is the risk of fire or electric shock!

Temperature at mounting location: -20°C up to +50°C.
Storage temperature: -25°C up to +70°C.
Relative humidity:
annual average value <75%.

1 NO contact not potential free 10A/250V AC. Incandescent lamps up to 2000 W, energy saving lamps ESL and LED lamps up to 200W. Switch-off early warning and permanent light by pushbutton switchable. Standby loss 0.7 walt only. With ESL optimisation.

Built-in device for installation.

45 mm long, 45 mm wide, 18 mm deep. **Zero passage switching** to protect contacts and lamps. This prolongs in particular the lifetime of energy saving lamps.

## By using a bistable relay coil power loss and heating is avoided even in the on mode.

The switched consumer may not be connected to the mains before the short automatic synchronisation after installation has terminated.

Control voltage, supply voltage and switching voltage 230 V. In addition electrically isolated universal voltage from 8 to 230 V UC.

With infinitely variable time range from 1 to 12 minutes.

50 mA glow lamp current, dependent on the ignition voltage of the glow lamps. 3-wire and 4-wire circuits, resettable, with attic lighting if 4-wire circuit. Automatic detection of the method of connection

After a power failure the lighting is switched on again in case the set time has not elapsed yet.

## Function rotary switches



$$\begin{split} \mathbb{T} &= \text{Switch-off early warning function} \\ &\stackrel{\text{\tiny{def}}}{=} \text{Permanent light by pushbutton} \\ &\mathbb{T} &\stackrel{\text{\tiny{def}}}{=} \text{Switch-off early warning function and permanent light by pushbutton} \end{split}$$

If switch-off early warning function  $\,^{\,}$ U is switched on, the light starts flickering approx. 30 seconds before time-out and is repeated three times at decreasing time intervals.


If permanent light by pushbutton \$\text{\$\text{\$}}\$ is switched on, permanent light can be switched on by pressing the pushbutton longer than 1 second. This is switched off automatically after 60 minutes or by pressing the pushbutton longer than 2 seconds.


If both switch-off early warning function and permanent light by pushbutton 'I' : are switched on, the switch-off early warning function is activated before the permanent light switches off.

When energy saving lamps ESL are completely or partially switched, then set the switch-off early warning with the pushbutton permanent light ESL on the lower rotary switch.


If the function TLZ is selected the **time** can be **extended** within the first second after switching on or resetting by pressing the pushbutton repeatedly up to three times (incrementing). Each momentary-contact control increments the set time once.

The function **ESV**, impulse switch with release delay up to 120 minutes, can be selected optionally. If this function is set it is automatically disconnected after the set delay is timed out if a manual OFF command has not been given. If the timing period is set to minimum in the function **ESV**, the release delay is switched off. The standard impulse switch function **ES** is then set.





4-wire circuit with, attic lighting, resettable



1) For lamps with 150W max

\* EVG = electronic ballast units; KVG = conventional ballast units

Must be kept for later use!

## Eltako GmbH

D-70736 Fellbach

## Technical Support English:

☎ Michael Thünte +49 176 13582514

⊠ thuente@eltako.de

€ Marc Peter +49 173 3180368

⊠ marc.peter@eltako.de

eltako.cor

27/2017 Subject to change without notice.