## Tap-radio<sup>®</sup> relay actuator TF61R-230 V





## TF61R-230V Tap-radio® relay actuator

Wireless relay actuator 10 A/250 V AC, 45x45x18 mm. 1 NO contact or NC contact, not potential free. Standby loss only 0.8 watt. Smart Home actuator.

Using easy tap-radio® technology, up to 32 wireless pushbuttons and wireless window contacts can be taught in. In addition the actuator can be locally controlled with a conventional 230 V wired pushbutton without glow lamp. During teach-in, the contact function in idle state can be defined as NO contact or NC contact. Closes the contact with at least one open window; it can then activate extraction hoods etc. or generate an alarm. Opens the contact with at least one open window: it can then switch off heaters or air conditioners.